

MNEAC-2P : 120/240V AC, 2-Pole, DIN Rail Breakers



Price: CAD \$49.99

SKU: MNEAC-2P

Product Categories: [Fuses & Breakers](#), [Supply](#), [Wiring & BOS](#)

Product Tags: [120V](#), [15A](#), [20a](#), [25A](#), [30A](#), [35a](#), [40a](#), [50A](#), [60a](#), [ac](#), [ac breaker](#), [branch](#), [breaker](#), [canada](#), [din rail](#), [midnite](#), [midnite solar](#), [mneac15-2p](#), [mneac20-2p](#), [mneac25-2p](#), [mneac30-2p](#), [mneac35-2p](#), [mneac40-2p](#), [mneac50-2p](#), [mneac60-2p](#), [solar](#)

Product Page:

<https://www.modernoutpost.com/product/mneac-120240v-ac-2-pole-din-rail-breaker-s/>

Product Variants

- MNEAC-2P : 120/240V AC, 2-Pole, DIN Rail Breakers - 15A ()
- MNEAC-2P : 120/240V AC, 2-Pole, DIN Rail Breakers - 20A ()
- MNEAC-2P : 120/240V AC, 2-Pole, DIN Rail Breakers - 25A ()

- MNEAC-2P : 120/240V AC, 2-Pole, DIN Rail Breakers - 30A ()
- MNEAC-2P : 120/240V AC, 2-Pole, DIN Rail Breakers - 35A ()
- MNEAC-2P : 120/240V AC, 2-Pole, DIN Rail Breakers - 40A ()
- MNEAC-2P : 120/240V AC, 2-Pole, DIN Rail Breakers - 50A ()
- MNEAC-2P : 120/240V AC, 2-Pole, DIN Rail Breakers - 60A ()

Product Summary

The Midnite Solar MNEAC-2P breakers are 120/240VAC, 2-pole, din rail mount breakers designed for use in AC branch circuit breaker boxes.

Product Description

The Midnite Solar MNEAC-2P 120/240V AC, 2 Pole, DIN Rail Breakers. Designed for use in AC branch circuit breaker boxes.

All MidNite circuit breakers are rated for 100% continuous duty. MidNite's breakers are rated to break the full rated load at the rated voltage repeatedly, with NO DAMAGE. Always use a properly sized breaker for disconnecting.

All MidNite MNEAC-2P circuit breakers can be used at 100% rated current when mounted in a MidNite enclosure.

Breaker Torque Value: 20 In-Lbs (2.3NM)

- Environmental Rating - Type 1 (Indoor) - Branch circuit rated - 15-25A models: 489A 10,000 AIC - 30A-60A models: Supplementary protection 1077. 3,000 AIC
- Listed for US & Canada

Product Attributes

- Dimensions: N/A
- Weight: .3 kg
- Amps Rating: 15A, 20A, 25A, 30A, 35A, 40A, 50A, 60A